Operator	Meaning
+	Result is src_1 + src_2
-	Result is src_1 - src_2
B-A	Result is src_2 - src_1
B	Result is src_2
~B	Result is the bitwise inversion of src_2
AND	Result is bitwise *and* of src_1 and src_2
OR	Result is bitwise *or* of src_1 and src_2
XOR	Result is bitwise *exclusive or* of src_1 and src_2
+carry	Result is src_1 + src_2 + carry from previous operation
-carry	Result is src_1 - src_2 - carry from previous operation
~AND	Result is bitwise (*not* src_1) *and* src_2
AND~	Result is bitwise (src_1 *and* (*not* src_2)
+8	Result is src_1 + src_2 with the first 24 bits set to zero
+16	Result is src_1 + src_2 with the first 16 bits set to zero